

Mobius Pro 2C (October 2020)

Firmware update to address sleep issues with Mac OS.

1. Connect a Mobius Pro 2C to a Windows computer. Disconnect all other external hard drives.
2. Download the firmware update tool: http://oyendigital.com/tech/firmware/Mobius_3R2-2C.zip
3. Extract the contents of the zip file to your computer.
4. Open the file: 'MPTool.exe'. (If Windows blocks it, select More Info>Run Anyway. Or right-click and select Properties>Unblock).
5. The utility will open and the Mobius will be listed. Click the 'play' button in the lower-left corner to begin the update process.

Note: The update will not delete data from the drive.

Asmedia MPTool Ver 2.2.0.0

Format: TYPE1 Vendor ID: 174C Product ID: 55AA Device Revision: 0100

Device Configuration: Input From Barcode, Input From HDDSN, S/N CHK, S/N Increase

Serial Number: [Empty] Manufacturer String: Oyen Product String: Mobius Pro 2C Idle Timer: Never

Device Function: USB Status: USB 2.0, MP Auto Mode, Update Config, Update FW, Reload FW, Partition / Format: Type: NTFS, Drive Label: NEW DISK, Partition Type: MBR, W/R Test, Preload Files, Speed Test, Read: [Empty] Write: [Empty], Auto Safe Remove After: 0 Seconds

FW Browser: 161028_B1_26_80.bin Preload Browser: C:\test

Port#	Status	VID	PID	Serial Number	FW Version	Capacity	Config Upd...	FW Update	ReLink	Partiti...	Format	R/W Test	Preload
0	SUP...	174C	55...	6PS3KFQG0000	151030b12602								
1													
2													
3													
4													
5													
6													
7													
8													

Pass: 0 Fail: 0 Total: 0 Progress: 0%

6. After completed, it will show the following FW version:

Asmedia MPTool Ver 2.2.0.0

Format: TYPE1 Vendor ID: 174C Product ID: 55AA Device Revision: 0100

Device Configuration: Input From Barcode, Input From HDDSN, S/N CHK, S/N Increase

Serial Number: [Empty] Manufacturer String: Oyen Product String: Mobius Pro 2C Idle Timer: Never

Device Function: USB Status: USB 2.0, MP Auto Mode, Update Config, Update FW, Reload FW, Partition / Format: Type: NTFS, Drive Label: NEW DISK, Partition Type: MBR, W/R Test, Preload Files, Speed Test, Read: [Empty] Write: [Empty], Auto Safe Remove After: 0 Seconds

FW Browser: [Empty] Preload Browser: C:\test

Port#	Status	VID	PID	Serial Number	FW Version	Capacity	Config Upd...	FW Update	ReLink	Partiti...	Format	R/W Test	Preload
0	SUP...	174C	55...	6PS3KFQG0000	161028b55502			PASS	PASS				
1													
2													
3													
4													
5													
6													
7													
8													

Pass: 1 Fail: 0 Total: 1 Progress: 100% **PASS**

7. Cycle the power on the Mobius. The firmware is now updated.